

## Lighting Your Life Since 1970

Product Specifications - 39650SHBZ				
Job Name:	Job Type:			
Quantity:	Comments			



## 39650SHBZ Mystic 11-Light Flush Mount

Finish Glass/Shade
Bronze Scotch Crystal

Lamping **Number of Bulbs** 11 **Light Type** LED **Bulb Type** PCB Max Bulb Wattage 2.8 **Max Fixture Wattage** 30.8 Rated Life **Rated Lumens** ±2,156 ±3,000 K **Color Temp** Bulb(s) Included Light Up/Down N/A **Beam Spread** N/A CRI 80 **Photo Cell Included** N/A Ballast/Driver/Transformer Yes

**Dimmable** 

Measurements	
Width	16.00"
Height	6.00"
Length	16.00"
Extension	N/A
Back Plate Width	N/A
Back Plate Height	N/A
HCO	N/A
Min Overall Height	0.00"
Max Overall Height	N/A
Hanging Weight	2.28 lbs
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	15.75"
Canopy Height	3.15"

15.75"

Product Category			
Flush Mount			

Shipping	
Carton Weight	3.90 lbs
Carton Width	19'
Carton Height	11'
Carton Length	19'
Carton Cubic Feet	2.28
Master Pack	1
Master Pack Weight	N/A
Master Pack Width	N/A
Master Pack Height	N/A
Master Pack Length	N/A
Master Cubic Feet	N/A
UPS Shippable	Yes

Certification Other Equivalents

**Canopy Length** 

Standard/Lutron® CL or Leviton® LED Recommended

Safety Rating	Dry	UPC Code	783209122987	Incandescent Watts	N/A
Energy Star	No	Shades Included	N/A	Fluorescent Watts	N/A
CA Title 24	Yes	Crystals Included	N/A		
CA Title 20	No	Diffuser Included	N/A		
ADA	No	Conversion Kit	N/A		
Dark Sky	N/A	Material	Metal+Crystal		

Maxim Lighting International and all designs, logos and images © 2016 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.