## **ASSEMBLY INSTRUCTIONS**








TO assemble safety cables: 1. Join fixture safety cables with cafety cable from ceiling.

2.Wrap both safety cable around the cable lock mut.

3.Insert screws into both holes on cable lock nut.secure screws with screwdrive.







Outlet box



Item # SN 4001

WE RECOMMEND INSTALLATION OF THIS LIGHTING FIXTURE BE DONE BY A LICENSED ELECTRICIAN.

WARNING\*\*\*SWITCH OFF THE MAIN ELECTRICAL SUPPLY FROM THE MAIN FUSE BOX/CIRCUIT BREAKER BEFORE INSTALLATION.

INSPECT ITEM CAREFULLY BEFORE ATTEMPTING TO INSTALL. IF THERE IS ANY DAMAGE OR OBVIOUS DEFECT. DO NOT INSTALL.

ITEM MAY NOT BE RETURNED ONCE IT HAS BEEN INSTALLED.

NOTE: CAREFULLY UNPACK EACH PIECE IN TOP LAYER OF PACKING PRIOR TO REMOVING. RETAIN ALL PACKING MATERIAL UNTIL INSPECTION AND INSTALLATION ARE FINAL.

- 1. Carefully remove all parts from the box.
- 2. Thread the fixture body (E) to the threaded ring (F).
- 3. Remove the mounting plate (B) from the fixture body (E) by loosening side screws (D).
- 4. Affix mounting plate (B) onto the outlet box and secure with mounting screws (C).
- 5. Connect the hot wire (BLACK) from the fixture to the hot wire from the outlet box (usually BLACK). Fasten them together with a plastic wire connector (A) provided and wrap the connection with electrical tape.
- 6. Connect the neutral wire (WHITE) from the fixture to the wire from the outlet box (usually WHITE).
  - DO NOT REVERSE THE HOT AND NEUTRAL CONNECTIONS OR SAFETY WILL BE COMPROMISED.
- 7. Connect ground wire from the fixture (bare copper) to ground wire from the outlet box (usually green or copper in color).

IT IS IMPERATIVE THAT THIS FIXTURE BE GROUNDED.

- 8. Tuck these wire connection neatly into ceiling with screws.
- 9. Attach the fixture body (E) onto the mounting plate (B) and secure with side screws (D).
- 10. Attach the crystals (I) onto the metal ring (H) with the metal string (J1).
- 11. Attach the metal ring (H) to the metal ring (Q) with the hook (G).
- 12. Insert bulbs (not included) into the sockets.
- 13. Installation is complete, turn on power at fuse or circuit breaker.









<sup>\*\*\*</sup>Clean with a dry, soft cloth only. Use no harsh abrasives or chemical agents.