

1500 Cherokee Parkway, Suite 100, Acworth, GA 30102

Phone: (866) 845-5451 • Fax: (866) 816-6165

Email: service@acclaim-lighting.com • www.acclaim-lighting.com

IN10056 INSTALLATION INSTRUCTIONS

Please read carefully and save these instructions, as you may need them at a later date.

CAUTION

WARNING: Risk of Fire. Consult a qualified electrician to ensure correct branch circuit conductor. Min 90°C supply conductors.

Turn off the main power at the circuit breaker before installing the fixture, in order to prevent possible shock.

GENERAL

All electrical connections must be in accordance with local and National Electrical Code (N.E.C.) standards. If you are unfamiliar with proper electrical wiring connections obtain the services of a qualified electrician.

Remove the fixture and the mounting package from the box and make sure that no parts are missing by referencing the illustrations on the installation instructions.

ASSEMBLY AND INSTALLATION

- 1. Attach the top rod (17) to the top open loop (16). Attach the bottom rod (19) to the bottom open loop (18). Repeat the process until all twelve rods are in place.
- 2. Attach chain (15) to loop (14) and screw collar loop (11), then close the chain (15) with chain pliers (not provided).
- 3. Pull out the outlet wire and ground wire from the outlet box (1). Make wire connections.
- --Ribbed wire (w/o marking) from light to White wire (2) from power source.
- --Smooth wire (w/o marking) from light to Black wire (3) from power source.
- -- Loop the ground wire (4) to mounting crossbar (6) with a ground screw (7).
- 4. Secure the mounting crossbar (6) to the outlet box (1) with mounting screw (8). Thread hex nut (9) onto nipple (10), then thread the nipple (10) into the mounting crossbar (6). Secure with the hex nut (9).
- 5. Slide screw collar loop (11) over canopy (12). Thread screw collar loop (11) into the threaded ring (13) and then onto nipple (10). Secure threaded ring (13).
- 6. Install bulbs: (bulbs not included)
- (Do not exceed the maximum capacity recommended on the sockets).

