

Project:		
Fixture Type:		
Location:		
Contact:		

P2144-1530K9

# Three-Light Bath

Wall mounted • Damp location listed PROGRESS LED

Images:





## **Description:**

Three-Light LED modern wall fixture in Polished Chrome with geometric frosted glass shades and a replaceable LED module. This modern fixture is perfect for the bathroom. 3000K color temperature and 90 plus CRI.

- Polished Chrome (-15) (plated)
- Steel Construction

**Specifications:** 

- Etched glass shades
- LED Module is replaceable (part # 93054049)
- · Provides evenly diffused illumination for vanity applications.
- · Geometric frosted glass shades.
- · Features a replaceable LED module.
- 623 lumens 69.2 lumens/watt per module (source)
- · 3000K color temperature, 90+ CRI.
- · Dimmable to 10% brightness (See Dimming Notes)
- Back plate covers a standard 4" octagonal recessed outlet box
- Mounting strap for outlet box included
- 6" of wire supplied
- · ENERGY STAR® qualified

### Performance:

Number of Modules	3	
Input Power	9w per module	
Input Voltage	120 V	
Input Frequency	60 Hz	
Lumens/LPW (Source)	623/69.2 (LM-82) per module	
Lumens/LPW (Delivered)	1684.95/70.5 (LM-79)	
CCT	3000 K	
CRI	90 CRI	
Life (hours)	60,000 (L70/TM-21)	
FCC	Meets FCC Title 47, Part 15 Class B	
Min. Start Temp	-30 °C	
Max. Operating Temp	30 ℃	
Warranty	5 year warranty	
Labels	cCSAus Damp location listed	
	ENERGY STAR® qualified	

### **Dimensions:**

Width: 24" Depth: 4" Height: 4-3/4"

H/CTR: 2-3/8" (glass facing up)

Glass Width: 3-1/4" Length: 6" Height: 3-7/8"



# Three-Light Bath

Wall mounted • Damp location listed PROGRESS LED



# P2144-1530K9

## **Dimming Notes:**

P2144 is designed to be compatible with many ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

## **Dimming Controls**

Lutron Nova T NTELV-300

Lutron Vierti VTELV-600

Lutron Ariadni AYCL-153P

Lutron Diva DVCL-153P

Lutron Maestro MAELV-600

Lutron spacer/system SPSELV-600

Leviton Renoir II AWRMG-EAW

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.