

Project:		
Fixture Type:		
Location:		
Contact:		

Two-Light Close-To-Ceiling

Wall or ceiling mounted • Damp location listed PROGRESS LED



Description:

Helm is a uniquely styled series with design flexibility. This contemporary square fixture has an acrylic diffuser with architectural detail. Can mount to ceiling or wall. Two-light LED fixture. 3000K, 90+CRI 1,211 Lumens 71.2 lumens/watt per module (source).

P3448-0930K9

Images:

Specifications:

- Brushed Nickel (-09) (plated)
- Steel Construction
- White acrylic diffuser
- LED Module is replaceable (part # 93053641)
- · Helm is a uniquely styled series with design flexibility.
- · This contemporary square fixture has an acrylic diffuser with architectural detail.
- · Can mount to ceiling or wall.
- 1,211 lumens 71.2 lumens/watt per module (source)
- · 3000K color temperature, 90+ CRI.
- · Dimmable to 10% brightness (See Dimming Notes)
- Back plate covers a standard 4" octagonal recessed outlet box
- Mounting strap for outlet box included
- 6" of wire supplied
- Complies with "Americans with Disabilities Act" ADA
- · ENERGY STAR® qualified



Performance:

Number of Modules	2	
Input Power	17w per module	
Input Voltage	120 V	
Input Frequency	60 Hz	
Lumens/LPW (Source)	1211/71.2 (LM-82) per module	
Lumens/LPW (Delivered)	1345/39.8 (LM-79)	
CCT	3000 K	
CRI	90 CRI	
Life (hours)	60,000 (L70/TM-21)	
FCC	Meets FCC Title 47, Part 15 Class B	
Min. Start Temp	-30 °C	
Max. Operating Temp	30 °C	
Warranty	5 year warranty	
Labels	cCSAus Damp location listed	
	ENERGY STAR® qualified	

Dimensions:

Square: 14" Depth: 3-3/4" Height: 3-3/4" H/CTR: 7"

Glass

Width: 11-13/16" Height: 3-5/8"



Two-Light Close-To-Ceiling





P3448-0930K9

Dimming Notes:

P3448 is designed to be compatible with many ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron Nova T NTELV-300

Lutron Vierti VTELV-600

Lutron Maestro MAELV-600

Lutron spacer/system SPSELV-600

Leviton Renoir II AWRMG-EAW

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.