


# HR-837

## 2.5" Low Voltage Downlight Trim

# WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project:

Location:

### PRODUCT DESCRIPTION

Gimbal ring style adjustable trim for use with HR-800 series low voltage miniature housings.

### FEATURES

- Accommodates most LED MR16 or Halogen MR16 lamps
- Retention clips secure lens firmly to lamp
- 1W minimum load transformers
- Abrasion resistant powder coat paint or plated metal finish
- Clear lens included, see opposite page for replaceable lens options
- Suitable for damp locations.
- 5 year WAC Lighting product warranty

### SPECIFICATIONS

**Construction:** Powder coated or plated brushed nickel finish on die-cast aluminum. Inner die-cast aluminum trim body has three retention clips to firmly hold trim to housing. Tension spring holds lens firmly against the lamp.

**Light Source:** Accommodates most LED MR16 or Halogen MR16 lamps

**Standards:** UL & CUL Listed.

**Housings:** Non-IC housings require 3" of clearance from insulation on all sides. Accommodates ceiling thickness of up to 3/4" for remodel & 3/4" for new construction.


### ORDER NUMBER

Model	Finish
HR-837	<b>BK</b> Black
	<b>BN</b> Brushed Nickel
	<b>CB</b> Copper Bronze
	<b>CH</b> Chrome
	<b>WT</b> White

HR-837 -

Example: HR-837-BN

### FINISHES



### LED MR16 (ORDER SEPARATELY)

MR16LED-BAB	BK WT
-------------	----------

### LENSES & LOUVERS

Color Lens	LENS-16-	AMB BLU GRN RED YEL	Amber Blue Green Red Yellow	UV Filter Frosted Lens Spread Lens Beam Elongating Lens Honeycomb Louver	LENS-16-UVF LENS-16-FR LENS-16-SPR LENS-16-BEL LENS-16-HCL
------------	----------	---------------------------------	---	--	--

### Compatible Housings

Compatible Housings	Model	Installation	Output	Rating	Volt
	<b>HR-801</b>	Remodel			
	<b>HR-802</b>	New Construction	12V, 50W max		Non-IC 120V
	<b>HR-806**</b>	Remote Transformer Remodel	12V/24V, 35W max		
	<b>HR-800*</b>	Remote Transformer			

\*Remote Electronic Class 2 Transformer Required (Sold Separately) \*\*Remote Electronic or Magnetic Transformer Required (Sold Separately)

### WAC Lighting

www.waclighting.com

Phone (800) 526.2588 • Fax (800) 526.2585

### Headquarters/Eastern Distribution Center

44 Harbor Park Drive • Port Washington, NY 11050

Phone (516) 515.5000 • Fax (516) 515.5050

### Western Distribution Center

1750 Archibald Avenue • Ontario, CA 91760

Phone (800) 526.2588 • Fax (800) 526.2585