

## IN40067 INSTALLATION INSTRUCTIONS

Please read carefully and save these instructions, as you may need them at a later date.

## CAUTION

WARNING: Risk of Fire. Consult a qualified electrician to ensure correct branch circuit conductor. Min 90°C supply conductors.

Turn off the main power at the circuit breaker before installing the fixture, in order to prevent possible shock.

## GENERAL

All electrical connections must be in accordance with local and National Electrical Code (N.E.C.) standards. If you are unfamiliar with proper electrical wiring connections obtain the services of a qualified electrician.

Remove the fixture and the mounting package from the box and make sure that no parts are missing by referencing the illustrations on the installation instructions.

## ASSEMBLY AND INSTALLATION

- 1. Thread the nipple (8) to the mounting plate (6) with lock nut (9).
- 2.Secure the mounting plate(6) with mounting screws (7) to the outlet box(1).
- 3.Pull out the outlet wire and ground wire from the outlet box(1).Make wire connections
- --Ribbed/White wire (w/o marking) from light to White wire(2) from power source.
- --Smooth/Black wire (w/o marking) from light to Black wire(3) from power source.
- --Loop the ground wire to mounting plate(6) with a green screw(5).
- 4. Attach the back plate(10) to the mounting plate(6) by inserting the nipple (8), then secure with nut (11).
- 5. Install bulbs: (bulbs not included)

(Do not exceed the maximum capacity that recommended on the socket).



1. OUTLET BOX

- 2. WHITE WIRE
- 3. BLACK WIRE
- 4. GROUNDING WIRE
- 5. GREEN SCREW
- 6. MOUNTING PLATE
- 7. MOUNTING SCREW
- 8. NIPPLE
- 9. LOCK NUT
- 10. BACK PLATE
- 11. NUT

INSTALLATION IS NOW COMPLETED