Ceiling Canopy

CNM13AC

START FROM HERE

- $\ensuremath{\cdot}$ Make sure $\ensuremath{\mathsf{POWER}}$ is $\ensuremath{\mathsf{COMPLETELY}}$ OFF at the fuse box
- Have your fixture installed by a qualified licensed electrician
- Prepare everything in a clear area
- Wear gloves at all time during this installation
- Read instructions carefully before you start assembly
- Keep this installation sheet for future reference

Technical Support: 1-855-855-8926

- 1. Remove fixture from its original package
- 2. Remove cover (1f) from canopy (2a)
- **3.** Attach canopy (2a) to electrical junction box (1a) using screws provided (1e) in hardware package
- Determine desired shade location, secure anchor (3a) into ceiling and lock ceiling hook adapter (3b) in place with screw (3c)
- **5.** Remove lamp shade **(3f)** from its original package, remove canopy attached from wire
- **6.** Attach wire gripper (**3e**) to ceiling hook adapter (**3b**) and fine tone height of pendants and lock in place with set screw and allan key (**3e**)
- **1.** Bring shade wires to canopy through strain relief (2c), secure with set screw and Allan key (2d)
- Cut and strip excess wire, push lever on terminal block (2b), make electrical connection for lamp shade (3f)
- Make proper electrical connections (black to hot "L", white to neutral "N", ground to "GND") with wire nuts (1b) provided in hardware package
- **10.** Attach cover (1f) to canopy (2a) and if applicable, insert lamp (3g) into socket

Please Note:

- This Kuzco LED fixtures come with pre-wired LED module(s)
- ${\boldsymbol{\cdot}}$ Unless instructed, Do Not touch any part of the LED module(s) as any unnecessary
- contact with the module could cause permanent damage • Dimming options depends on choice of pendants
- 2b. 1a. 2c. 1b. 2a. 2d. 1e 1f. 3a. 3b. 3c. 3d. 3e. 3f. 3g

19054 28th Avenue Surrey, BC Canada V3Z 6M3 T: 604 538 7162 TF: 1-855 85 KUZCO F: 604 538 7196 W: kuzcolighting.com 20200103