## NX-811-LED Surface Mount Adjustable LED Edge-Lit Exit Sign with 90° Adjustability, 2-Circuit

Lamp: LED Source

#### **PRODUCT DESCRIPTION**

Architectural acrylic edge-lit sign for applications requiring low-profile, yet decorative appearance. Uses included, but are not limited to museums, galleries, office building lobbies, etc. Incorporates 25+ year LED source. AC, 2-Circuit, with letters in either green or red color.

#### BODY

Extruded aluminum housing and acrylic panel.

#### FACE

Edge-lit Exit is available in either single or double face. Face is constructed with 0.40 clear acrylic with rounded and finished edge for attractive appearance. Face contains red or green 6" high and 3/4" thick lettering inside face to comply with ETL/NFPA requirements. Reflective stick-on chevrons provided and are applied to rear of panel in order for light to reflect off the inner face of the chevron tape to provide a similiar effect as the lettering embedded inside the acrylic. Face can be adjusted in the field from 0° to 90° for wall, ceiling or sloped applications.

#### MOUNTING

Mounting hardware consist of 0.06 steel universal junction box bracket, 7/8" profile 0.11 diecast aluminum bracket cover, screws, wire nuts, and silver-finished plastic plugs that are used to eliminate remaining knocouts once mounting configuration is selected.

#### ELECTRICAL

Input: Dual 120V/277V (0.038A / 0.017A) Wattage: 3 Watts normal / 5 Watts emergency operation Light Source: Long life LED sources Testing: High charge / ready operation indicator light with test button and automatic reset Circuit Protection: Isolated surge / short circuit protection (Disconnect for deep discharge) Life Expectancy: 25 Years with no change in illumination level

#### **EMERGENCY CIRCUIT**

2nd Circuit for input from external EPS or other alternative emergency power source or generator

#### LABELS AND LISTINGS

ETL Listed NEC NFPA State & Municipal 5 Year Warranty on materials and worksmanship

#### ACCESSORIES

NEXC-G: Replacement Green Chevrons NEXC-R: Replacement Red Chevrons

# **ENORA**LIGHTING.

Туре


Project

Catalog No.

### Lamp/Wattage

#### DIMENSIONS

NX-811-LED



Heigth : 10-5/8" Width : 12" Depth : 1-5/8"



LED Exit Sign Catalog No. Letter Color Pannel Style Housing				
NX-811	R = Red	<b>C</b> = Clear One Side	<b>A</b> = Aluminum	
	$\mathbf{G} = Green$	$\mathbf{M} = \mathbf{M}$ irror One Side	$\mathbf{W} = \mathbf{W}$ hite	
		<b>2M</b> = Double Face Mirror	$\mathbf{B} = Black$	

Create a complete track head number: Example: NX-811-LED/RCA



6505 Gayhart St., Commerce, CA 90040 • Phone: 800.686.6672 • FAX: 800.500.9955 • www.noralighting.com e-mail: nora@noralighting.com • Specifications subject to change without notice. © 2014