# IAMP

PRODUCT FEATURES

- This small yet powerful rechargeable lamp fits in just about any spot, great for restaurant dining tables
- Designed with an integrated 3-step touch-dimmer.
- 12-14 hours of battery life, allowing use for extended periods without worrying about running out of power
- 5- hour charging time
- Modern finishes available



Includes 120-240V 2.1 watts, 176 delivered lumens, 90 CRI 2700K LED module. Built-in three way dimming. Black or bronze includes black cable. White includes white cable. Natural Brass includes cream cable. 6 feet of USB C to C cable. Wall charger included.



Matte White







Hand Rubbed Antique Brass

Black

### ORDERING INFORMATION


SLTB534	COLOR TEMP	FINISH	
	27 2700K	В	BLACK
		ΒZ	BRONZE
		HAE	B HAND-RUBBED ANTIQUE BRASS
		W	MATTE WHITE

SLTB534	
JOB NAME	
NOTES	



### **SPECIFICATIONS**

PRIMARY MATERIAL	Brass
SHADE MATERIAL	Aluminum or Brass
NET WEIGHT	1.5 lbs
HEIGHT	10in
WIDTH	5.1in
LENGTH	5.1in
WET LISTED	
DAMP LISTED	
DRY LISTED	
GENERAL LISTING	ETL Listed
INCLUDES	



### LAMPING SPECIFICATIONS

	LED LAMP	INTEGRATED LED	NON LED	NO LAMP		
DELIVERED LUMENS		176				
WATTS		2.1				
MAX WATTAGE PER BULB		2.1W				
		120V-240V Integrated 3-Step Tou	120V-240V Integrated 3-Step Touch Dimmer			
ССТ		2700K				
CRI		90 CRI				
LED LIFETIME						
L70		>50000				
AVERAGE BULB HOURS						
FIELD SERVICEABLE LED						
LAMP BASE		Integrated LED	Integrated LED			
LAMP SHAPE		Integrated LED				
LAMP INCLUDED?		True				
WARRANTY**		1 Year				

<sup>\*</sup> Dimming information available at <a href="www.techlighting.com/Downloads#dimming">www.techlighting.com/Downloads#dimming</a>

## T20 / T24 / JA8 INFORMATION

	Integrated LED	Replacement LED Lamp	No Lamp *
This product can be used to comply with California Building Energy Efficiency Standards 2016 Title 24 Part 6/JA8.	No		
This product can be used to comply with California Appliance Efficiency Standards 2016 Title 20 and may be shipped to and sold in California.			

 $<sup>^{*}</sup>$  If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.



<sup>\*\*</sup> Visit techlighting.com for specific warranty limitations and details.